

HIGH-VOLTAGE INTEGRATED VERTICAL RESISTOR AND MANUFACTURING PROCESS THEREOF

TECHNICAL FIELD

The present invention relates to a high-voltage integrated vertical resistor
5 and to a manufacturing process thereof.

The present invention can advantageously, but not exclusively, be applied in
the manufacture of high-voltage resistors integrated in a semiconductor material body
together with power devices, to which the following description refers, without however
detracting from generality.

10 BACKGROUND OF THE INVENTION

As is known, high-voltage resistors integrated on a semiconductor material
substrate are used extensively in the field of integrated monolithic power devices, for
example devices manufactured using VIPower technology, according to which the power
devices are integrated in a first chip region, known as the power region, whereas the
15 corresponding control devices are integrated in a second chip region, which is known as the
control region, and is separated and electrically isolated from the power region.

In addition, in some applications, it is also necessary to have available
within the control region a biasing voltage which is branched from the biasing voltage of
the substrate, by means of a partition provided using a resistor connected between the
20 substrate and the control region.

However, in order for this resistor to be able to withstand the high values
(up to 2 kV) which, as is known, the biasing voltage of the substrate can reach, it must have
somewhat high resistance values which generally vary between 100 k Ω and a few M Ω .

A solution which is commonly used to manufacture a resistor having the
25 above-described resistance values consists of forming on the semiconductor substrate a
doped region with high resistivity and having conductivity opposite that of the
semiconductor substrate, and a flat coil pattern.

Although it is advantageous in various respects, this solution has the disadvantage that it requires a somewhat large surface area, owing mainly to the fact that, in order to prevent malfunctioning of the resistor, the minimum distance which must be maintained between two adjacent parallel branches of the coil resistor cannot be reduced as
5 required, but depends on the concentration of doping agent present in the substrate, and on the voltage across the resistor.

In fact, as is known, when the junction formed by the substrate and the resistor is biased inversely, the size of the depletion or space-charge region which consequently extends in the substrate, is inversely proportional to the concentration of
10 doping agent in the substrate, *i.e.*, it is directly proportional to the resistivity of the substrate.

Consequently, although the high-voltage resistor can be integrated using the most resistive layers available in the technique, devices manufactured using VIPower technology and able to withstand high voltages, have necessarily high resistivity in the
15 substrate, of several orders of magnitude greater than the most resistive layers available according to the present technological processes, and thus, the size of the depletion region extending in the substrate has somewhat large dimensions, of approximately tens of microns, when high differences of potential are applied.

From the foregoing, it is apparent that, in order to prevent the depletion
20 regions of two adjacent parallel branches of the coil resistor from coming into contact, and giving rise to the known pinch-off phenomenon, thus giving rise to deterioration of the resistance value of the resistor, and therefore of the functionality of the circuitry to which this resistor is connected, during the design stage it is necessary to space each pair of adjacent parallel branches of the coil resistor, by a value which is greater than the sum of
25 the maximum widths of the depletion region applicable for each branch.

In order to reduce the depletion region present between the various branches, a known solution consists of enriching the layer designed for integration of the resistor. However, this solution reduces the breakdown voltage of the device, since, in order to be able to obtain the required reduction of the depletion region, it would be
30 necessary to have an extremely high concentration of doping agent.

The aforementioned large surface area of the coil resistor is also caused secondarily by the fact that the presence of high voltages on the resistor requires the formation of so-called edge structures which can protect against phenomena of premature breakdown of the regions of the resistor subjected most to the high voltages. In fact, for
5 example, for this purpose, so-called metal field plates are formed, *i.e.*, annular regions with high resistivity (low concentration of doping agent) and surrounding the coil resistor.

A further effect which contributes towards making the surface area of resistors of the above-described type large, is their interaction with the edge structures of the devices in which they are used, and the consequent necessity to arrange this resistor in
10 the vicinity of the terminal region of the device from which the high voltage is obtained.

In order to reduce the depletion region present between the various branches of the coil resistor, a solution proposed recently, which is the subject of European Patent application 98830638.7 filed on October 23, 1998, by the same applicant, consists of forming the coil resistor using a semiconductor material layer with high resistivity and
15 having conductivity opposite that of the substrate, and, between each pair of adjacent parallel branches of the coil resistor, forming one or more isolation trenches, for example formed of silicon dioxide, extending in depth further into the substrate than the semiconductor material layer from which the coil resistor is formed, by an extent sufficient to prevent the pinch-off phenomenon from occurring.

However, also in this solution, the coil resistor is arranged close to the
20 terminal region of the device from which the high voltage is obtained, and consequently the reduction of the surface area is relatively small, and there still exists the disadvantage caused by the interaction of the resistor with the edge structures of the device in which this resistor is formed.

25 SUMMARY OF THE INVENTION

An embodiment of the present invention provides a high-voltage resistor and a manufacturing process thereof which make it possible to eliminate the above-described disadvantages.

An embodiment of the invention is directed to an integrated device that includes a resistor with a vertical current flow structure. The integrated device includes a semiconductor body having a surface; a doped semiconductor region extending longitudinally into the semiconductor body from the surface; and an insulating region extending longitudinally into the semiconductor body from the surface. The insulating region laterally surrounds the semiconductor region to laterally insulate the semiconductor region from electronic devices positioned laterally of the insulating region. Accordingly, the semiconductor region is the resistor and extending transversely with respect to the surface of the semiconductor body.

10 BRIEF DESCRIPTION OF THE DRAWINGS

In order to assist understanding of the present invention, some preferred embodiments are now described, purely by way of non-limiting example, and with reference to the attached drawings, in which:

Figure 1 shows a schematic transverse cross-section of a semiconductor material body in which there is provided a high-voltage vertical resistor according to a first embodiment of the present invention;

Figure 2 is a schematic plan view of the semiconductor material body in Figure 1;

Figure 3 shows a schematic transverse cross-section of a semiconductor material body in which there is provided a high-voltage vertical resistor according to a second embodiment of the present invention;

Figure 4 shows a schematic transverse cross-section of a semiconductor material body in which there is provided a high-voltage vertical resistor according to a third embodiment of the present invention; and

Figure 5 shows a schematic transverse cross-section of a semiconductor material body in which there is provided a high-voltage vertical resistor according to a fourth embodiment of the present invention.

DETAILED DESCRIPTION OF THE INVENTION

In Figures 1 and 2, 1 indicates as a whole a device integrated in a semiconductor material body 2 and comprising a resistor 4 according to a first embodiment of the present invention, and, purely by way of non-limiting example, a control transistor 6 with a horizontal structure, and a power transistor 8 with a vertical structure.

In particular, in order to manufacture the resistor 4, the control transistor 6 and the power transistor 8, on a substrate 10 of monocrystalline silicon with a high concentration of doping impurities of type N^+ , there is initially grown a first epitaxial layer 12 having a thickness and a concentration of impurities selected according to the maximum voltage which the resistor 4 must be able to withstand; typically, the concentration of the impurities present in the epitaxial layer 12 varies between 10^{13} and 10^{14} atoms/cm³, whereas the thickness of the epitaxial layer 12 is generally between 60 and 120 μm .

Then, by means of ionic implantation and a subsequent diffusion process, a first and a second buried region 14, 16 of type P^- are formed on the first epitaxial layer 12. In particular, the first buried region 14 is formed in a control area 20 of the semiconductor material body 2 in which the control transistor 6 is arranged, whereas the second buried region 16 is formed in a power area 22 of the semiconductor material body 2 in which the power transistor 8 is arranged.

The power area 22 is spaced from the control area 20, and together with the control area 20, delimits an intermediate area 24, which is thus arranged between the control area 20 and the power area 22, and in which the resistor 4 according to the present invention is formed.

On the control area 20, the power area 22 and the intermediate area 24, there is then grown a second epitaxial layer 26 of type N and having a thickness of between 2 and 10 μm .

At the intermediate area 24, using known photolithography and selective chemical etching techniques, for example the known technique of plasma etching, there is then formed in the second epitaxial layer 26 a trench 30, extending in depth beyond the buried regions 14, 16, and having, in plan view, a closed annular shape, which in this case

is shown in Figure 2 in the shape of a rectangular frame, and for example has a width of 1-3 μm and a depth of 10-100 μm .

An oxidation step is then carried out in order to form an oxide layer 32 covering the lateral walls and the base wall of the trench 30, and having a thickness which depends on the electrical performance levels required from the integrated device 1, for example of between 200 and 500 nm.

Subsequently, the trench 30 is completely filled with an isolating filler material 34. Alternatively, the oxidation step could also have a duration such as to form an oxide layer which fills the trench 30 completely.

At the upper surface of the portion of the second epitaxial layer 26 surrounded by the trench 30, by means of ionic implantation, there is then formed a region 36 of type N^+ with low resistivity, which is used to form a low-resistivity contact of the resistor 4.

The trench 30 thus formed is arranged between the control area 20 and the power area 22, and surrounds portions of the first and second epitaxial layer 12, 26, which define the resistor 4.

In particular, the resistor 4 has a structure and a current flow which are totally vertical, a resistance which depends on the volume of semiconductor material which is surrounded by the trench 30, and electrical behaviour which depends on the depth of the trench 30, and more particularly depends on the distance D between the base wall of the trench 30 and the PN junctions which the buried regions 14, 16 define with the first epitaxial layer 12.

In particular, the electrical behaviour of the resistor 4 can be controlled during formation of the trench 30 using a known physical phenomenon which is associated with the technique of plasma etching, and has hitherto been considered as a "deficiency" of plasma etching, which makes it possible to form trenches in the silicon at different depths, by varying only the area of silicon to be removed. To give an example, by means of a single photo-masking operation, it is possible to obtain trenches having an opening of 1.0 μm and a depth of 10 μm , and trenches having an opening of 3.0 μm and a depth of 20 μm .

In particular, the resistor 4 can be modelled substantially to comprise a fixed component and a variable component, shown in Figure 1 as a thin line, in the form of two resistors R1 and R2 connected in series. The fixed component is defined by the volume of semiconductor material contained by the trench 30, whereas the variable component is defined by the “useful” volume of semiconductor material present below the trench 30, *i.e.*, by the volume which has not been depleted of majority carriers from the depletion region, which extends in the epitaxial layer 12 below the trench 30, and is caused by the inverse biasing of the PN junctions which the buried regions 14, 16 define with the first epitaxial layer 1.

By this means, the resistor 4 has a mixed behaviour depending on the biasing voltage of the substrate, and the threshold for change of behaviour can be controlled by controlling the depth of the trench 30. In particular, the resistor 4 has linear behaviour for low substrate biasing voltages, *i.e.*, for which the depletion region does not invade the area of substrate below the trench 30, and thus the resistance of the resistor R2 does not vary, and behaviour of the JFET type for high substrate biasing voltages, *i.e.*, for which the depletion region invades the area of the substrate below the trench 30, and thus the resistance of the resistor R2 varies until it assumes a maximum value when the pinch-off occurs.

During manufacture of the resistor 4, in the control area 20 and in the power area 22, the control transistor 6 and the power transistor 8 are also manufactured.

In particular, as shown in Figures 1 and 2, in the control area 20, inside the second epitaxial layer 26, in a manner which is known and is thus not described in detail, there are formed the collector region 40 of type N^+ of the control transistor 6, the base region 42 of type P^+ , which is separated from the collector region 40 by a portion of the epitaxial layer 26, and, inside the base region 42, the emitter region 46 of type N^+ . In the second epitaxial layer 26, there is also provided a region 48 of type P^+ , which is formed along a perimeter area of the second epitaxial layer 26, and extends in depth as far as the first buried region 14, and which forms together with the latter a single region of type P^+ .

On the other hand, in the power area 22, inside the second epitaxial layer 26, there is formed a region 50 of type P^+ , which is identical to the region 48, and defines the

base region of the power transistor 8, and a region 52 of type N^+ , which defines the emitter region of the power transistor 8, the collector region of which is on the other hand constituted by the first epitaxial layer 12.

Subsequently, using known photolithographic and depositing techniques,
5 there are formed on the upper surface of the semiconductor material body 2 the electrical contacts and the electrodes associated with the latter, indicated as a whole as 54, of the resistor 4, the control transistor 6 and the power transistor 8, whereas on the lower surface of the semiconductor material body 2, there is formed a layer of metallization 56, which constitutes both the second electrode of the resistor 4, and the collector terminal of the
10 power transistor 8.

The advantages which the resistor 4 makes it possible to obtain, are apparent from examination of its characteristics.

Firstly, the resistor 4 can be integrated in any portion of an integrated power device, including inside the area occupied by an elementary component, thus preventing
15 problems relating to interaction with the edge structures of the device, and in order to manufacture it, additional layers are not required, since use is made of the layers which are already present in the process sequence of the power device.

Since the resistor 4 has a completely vertical structure, it occupies a space which is considerably reduced in comparison with that of the resistors produced according
20 to the known art, since it is surrounded by a trench, the overall width of which can vary between 1 and 3 μm .

In addition, the resistor 4 has a single low-voltage electrode arranged on the upper surface, whereas the high-voltage electrode consists of the substrate, which has the electrical contact arranged on the rear of the semiconductor material body 2.

25 In addition, the resistor 4 has the same conductivity as that of the substrate in which it is formed, unlike the case according to the known art, in which, as initially described, the coil structure is formed with conductivity opposite that of the substrate in which it is formed.

This further difference from the resistors manufactured according to the
30 known art means that in the resistor 4, there is no longer present a depletion region caused

by the inverse biasing of the PN junction which it forms together with the substrate, and this gives rise to a considerable reduction in the associated parasitic effects (and which in general can be modelled with parasitic capacitance), which in turn provides the resistor with real ohmic behaviour which is closer to an ideal ohmic behaviour than is the case for the resistors manufactured according to the known art.

According to a further aspect of the present invention, in the portions of semiconductor material surrounded by the trench 30, it is also possible to form other elementary components with a vertical structure, arranged in series with the resistor 4, which make it possible to obtain more complex operating modes.

Some examples are shown in Figures 3-5. In particular, Figure 3 shows an integrated device, indicated as 1', the substantial parts of which are identical to the integrated device 1, and which differs from the latter only in that it does not comprise the area 36 with low resistivity provided in the intermediate area 24, on the upper surface of the second epitaxial layer 26.

By this means, the metal semiconductor junction defined firstly by the metal contacts, and secondly by the second epitaxial layer 26, forms a Schottky diode, which is shown as a thin line and is indicated as DS, connected in series to the resistors R1 and R2.

On the other hand Figure 4 shows an integrated device, indicated as 1'', the substantial parts of which are identical to the integrated device 1, and which differs from the latter only in that the region with low resistivity which is provided in the intermediate area 24 on the upper surface of the second epitaxial layer 26, and is indicated in this case as 36'', has conductivity opposite that of the second epitaxial layer 26, and in particular conductivity of type P⁺.

By this means, the region 36'' with low resistivity and the second epitaxial layer 26 form a Zener diode, which is shown as a thin line and is indicated as DZ, connected in series to the resistors R1 and R2, and which, with its characteristic breakdown, determines the threshold of intervention of the resistors R1 and R2.

Finally, Figure 5 shows an integrated device, indicated as 1''', the substantial parts of which are identical to the integrated device 1, and which differs from the latter in that:

the filler material for the trench 30, indicated here as 34"', is of the conductive type, for example doped polysilicon;

instead of the two buried regions 14, 16 there is a single continuous buried region, indicated in Figure 5 as 15, which is formed by means of a single ionic
5 implantation and diffusion and is then interrupted by the trench 30, such that a portion is surrounded by the trench 30; and

in the portion of the second epitaxial layer which is surrounded by the trench 30, there is formed a region, indicated as 27, which has conductivity opposite that of the first epitaxial layer 12 and of the region 36 with low resistivity, in this case of
10 type P^+ , and which occupies completely the volume between the region 36 and the buried region 15.

By this means, the region 36, the region 27, the oxide layer 32, the filler material 34 and the buried region 15 define a pair of MOSFET transistors, shown in Figure 5 as a thin line and indicated as M1 and M2, connected in the manner illustrated in Figure
15 5, and the channel region of which is formed by the region 27.

When they are switched on, the MOSFET transistors M1, M2 make it possible to control not only the threshold of intervention of the resistor 4, but also the flow of current which passes through the latter.

Finally, it is apparent that modifications and variants can be made to the
20 production process described and illustrated here, without departing from the protective scope of the present invention.

For example, in the case of devices in which formation of the control transistor 6 and the power transistor is not required, the buried regions 14, 16 and the second epitaxial layer 26 can be omitted, and thus the trench 30 can be formed directly in
25 the first epitaxial layer 12.

In addition, the substrate 10 and the first epitaxial layer 12 can be replaced by a single substrate of the float zone type, which has a profile with concentration which decreases from the lower surface towards the upper surface of the substrate, on which either the resistor according to the invention can be formed, or the second epitaxial layer 26
30 can be grown.

In addition, in the integrated device 1''' according to the third embodiment of the present invention, the region 27 having conductivity P^+ could also be omitted, and thus the channel of the MOSFET transistors M1 and M2 could be formed by the portion of the second epitaxial layer 26, as well as the region 36 with low resistivity, such as to form a
5 Schottky diode.

0
1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
2220
2221
2222